

SUITABLE FOR MODEL

IMAGE MAY VARY FROM ACTUAL PRODUCT

SAFETY INSTRUCTION**READ CAREFULLY BEFORE INSTALLING FIXTURE. PLEASE KEEP THIS MANUAL FOR FUTURE USE.**


Fixtures must be wired in accordance with the National Electrical Code and all applicable local codes. Proper grounding is required for safety.

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. MAKE CERTAIN POWER IS OFF BEFORE INSTALLING OR MAINTAINING FIXTURE.


CHECK THAT VOLTAGE IS COMPATIBLE WITH FIXTURE DRIVER. USE APPROVED CONNECTORS FOR ALL ELECTRICAL CONNECTIONS.

Maintenance Caution

1. Review the wire connection before beginning, and make sure fixture is grounded properly.
2. For lighting controls, follow control instructions carefully.
3. Turn power off and wait for fixture to cool before performing maintenance.
4. Maintenance must be done by professionals.


WIRE CONNECTION**UNIVERSAL VOLTAGE 120-277V**

WITH PHOTO CONTROL:120V/277V




INSTALLATION

OPTION 1: TRUNNION INSTALLATION




1. Attach the trunion to the body by M4*10 screws.
2. Attach the wires to the waterproof joint.
3. Attach the trunion to the wall and connect the wires.

OPTION 2: KNUCKLE INSTALLATION



1. Connect the power.
2. Attach the luminaire by knuckle and screw 1/2 NPS nut tightly.

OPTION 3: JUNCTION BOX INSTALLATION



1. Open the connection box cover, drill the holes in the area of installing holes.
2. Attach the holder to the body by M4*10 Screw A.
3. Pass the wires through waterproof joint to the connection box and use the waterproof joint to tighten the wires.
4. Attach the connection box to the wall.
5. Connect the wires in the connection box and screw the cover tightly.
6. Adjust the direction of the body as request, and tighten the M4*10 Screw B.